



Utility Radio			
MODEL			LUNCH BOX
TUNING	Type		PLL synthesized
	Memory Presets		FM x 5 / AM x 5
	Rotary Tuning		V
DISPLAY	Type		LCD (TN)
	Size (mm)		57x25
	Back light		V
BAND	FM	Frequency (MHz)	87.5-108
	MW	Frequency (kHz)	520 - 1710
AUDIO TONE		Deep bass compensation	V
OUTPUT DEVICES		Speaker unit	5.25 inches 8 ohm
OUTPUT POWER (TYPICAL)	AC / DC in (Speaker)		5W
	Batteries (Speaker)		2.5W
POWER SUPPLY	AC - USA		120V 60 Hz
	AC - EUR		230V 50 Hz
	Batteries (Main power)		4x 1.5V (UM-2)
SPECIAL PERFORMANCE		Water resistance	JIS - 4
DIMENSIONS	Width (inch)		11.8
	Height (inch)		7.28
	Depth (inch)		9.05
	Weight (lb. oz)		6lb. 9.8oz